



DIN-RAIL ZONE MONITOR

FUNCTION

The DIN-Rail Zone Monitor powers and controls the operation of a zone of up to 20 conventional fire detectors from a loop of XP95 addressable detectors and ancillary devices.

FEATURES

The DIN-Rail Zone Monitor is factory preset to return an analogue value of 16 when all detectors on the zone are in the quiescent state and 64 when a detector changes to the alarm state. The unit latches in the alarm state.

A 6.2k Ω end-of-line resistor is used to monitor cables for open and short-circuit faults. Alternatively, an active end-of-line monitor may be used in conjunction with diode bases and a capacitor of up to 50 μ F fitted at the unit wiring terminals.

In either case an analogue value of 4 is transmitted during open or short-circuit faults.

The DIN-Rail Zone Monitor is fitted with a bi-directional short-circuit isolator and will be unaffected by loop short-circuits on either loop input or output.

ELECTRICAL CONSIDERATIONS

The DIN-Rail Zone Monitor is loop powered and operates at 17–28V DC with protocol pulses of 5–9V.

PROTOCOL COMPATIBILITY

The DIN-Rail Zone Monitor will operate only with control equipment using the Apollo XP95 or Discovery protocol.



Part no. 55000-812

Dimensions and weight of DIN-Rail Zone Monitor:
110 x 107 x 20mm 95g

Two DIN-Rail enclosures are available:
4 way 29600-239
10 way 29600-240



A HALMA COMPANY

© Apollo Fire Detectors Limited 1998–2008

Overseas offices:

America | China | Germany | Ireland | Spain

36 Brookside Road, Havant,
Hampshire, PO9 1JR, UK.

Tel: +44 (0)23 9249 2412
Fax: +44 (0)23 9249 2754

Email: sales@apollo-fire.co.uk
Web: www.apollo-fire.co.uk

MECHANICAL CONSTRUCTION

The DIN–Rail Zone Monitor is supplied in a standard housing which is clipped onto a standard 35mm DIN rail (DIN 46277) or fixed directly to the enclosure using two 4mm screws.

Connections are made via plug-in terminal blocks which accept wires up to 2.5mm².

Two LEDs are visible through the top cover of the enclosure.

The red LED illuminates in the event of an alarm condition being detected.

The yellow LED is illuminated whenever the built in isolator has sensed a short-circuit loop fault.

EMC DIRECTIVE 89/336/EEC

The DIN–Rail Zone Monitor, Part No. 55000-812 complies with the essential requirements of the EMC directive 89/336/EEC, provided that it is used as described in this PIN sheet.

A copy of the Declaration of Conformity is available from Apollo on request.

Conformity of the DIN–Rail Zone Monitor with the EMC directive does not confer compliance with the directive on any apparatus or systems connected to it.

Technical Data

Loop voltage	17–28V DC
Zone voltage	
(Loop voltage > 22V)	19V ±1V
(Loop voltage < 22V)	loop voltage –1.5V
Maximum current consumption at 24V	
switch-on surge, max 150ms	2.8mA
quiescent	4mA + detector load
alarm	11mA
short-circuit	11mA
Maximum quiescent detector load	2mA
Maximum current through isolator	
	1A continuous 3A peak
Isolating voltage	14V
End-of-line resistor value	6.2kΩ + 5% 1/3W
Stabilisation time on power-up	4 seconds
Maximum capacitor on zone terminals	50µF
Operating temperature	–20° C to + 70° C
Humidity (no condensation)	0% – 95%
Shock, Vibration and Impact	EFGS/F/95/007
IP rating	20
EMC	Emissions BS EN 50081–1 1992
	Immunity BS EN 50130–4 1996

For further technical information please refer to PP2049-T, available on request.

Dimensional Drawing (mm)

