

FP2

MANUAL CALL POINT

The FP2 manual call point is a key resettable device which offers all commonly used switch monitoring configurations in one device.

Available in white, yellow and green for use in other applications such as Emergency Door Release.



- Available in red, green, white, yellow
- Available as double pole or single pole
- Key resettable
- For use in applications such as Access Control
- Lift up cover available
- Choice of wording available

Product codes

Code	Description
FP2/GR/DP/LU	FP2 Green Double Pole
FP2/GR/EDR	FP2 Green printed EDR
FP2/WH/DP/LU	FP2 White Double Pole
FP2/WH/EDR	FP2 White printed EDR
FP2/YL/DP	FP2 Yellow Double Pole
MOUFPC	FP2 Clear Left Up Cover

Technical data

Switch Type:	Single pole change over switch
Contact Rating:	10A/250V AC, 5A/30V DC Resistive Load (Max) 3A/250V AC, 2A/30V DC Inductive Load (Max)
Monitoring Resistor:	Selectable, 470 or 680 Ohm 1 Watt Carbon Film
Blocking Diode:	Selectable, Type IN4001 (50V)
L.E.D. Indication:	Selectable, Red L.E.D.
Terminal Type:	2.5mm insertion type, rated 10A/250V AC (2 per switch pole)
Mode Selection:	Cut link LK1, LK2 or LK3 to select resistor or diode options
I.P. Rating:	Designed to conform to I.P.44
Materials:	Case - ABS Plastic; Actuator - Polycarbonate

rev. 3-10/2019



www.cqr.co.uk

info@cqr.co.uk

Sales: +(0)151 606 1000 Tech: +(0)151 606 6311

CQR Security Ltd, 125 Pasture Road, Moreton, Wirral, CH46 4TH, UK

