

## LED Emergency Exit Sign

**Product Code -  
WBXELES3W**



**3W Maintained/Non-Maintained 3-hour Emergency Exit Sign**

**Complete with Full Legend Set**



# DATA SHEET



<b>Model</b>	<b>WBXELES3W</b>
<b>Input</b>	230 240Vac 50/60Hz $\pm$ 10%
<b>Light Source</b>	White LED
<b>IP Rating</b>	IP20
<b>Emergency Duration</b>	3 hours (minimum)
<b>Viewing Distance</b>	30M
<b>Mains Current (max)</b>	50-90mA (max) 35mA quiescent (3W)
<b>Recharge Period</b>	Less than 24 hours
<b>Charge Indicator</b>	Integral green LED
<b>Changeover Voltage</b>	As per requirements of BS EN 60598-1:2008
<b>Battery</b>	LifePo4 Battery
<b>Cable Entry</b>	16/20mm gland entry on 3 sides. BESA Box on rear
<b>Installation Aids</b>	Hinged Cover – Screwless Terminals
<b>Accessories</b>	Pictogram Legend Set (Supplied)

**Warranty 36 months**



VI.1 FOR MORE INFORMATION,  
CONTACT YOUR ADI SALES PERSON.

[www.adiglobal.com](http://www.adiglobal.com)